

Installing MRK-MST250 If you are using shorter (27mm) or longer (70mm) mSATA card, please use the instructions on page 2 to adjust the card mount.

1. Verify the package contents.

2. Attach mSATA Device by inserting the mSATA card and securing the two screws to hold the mSATA card in place.

3. Replace cover and secure with 4 screws.

4. The device is ready to be integrated into your system.

Installing UGT-MST100 If you are using shorter (27mm) or longer (70mm) mSATA card, please use the instructions on page 2 to adjust the card mount.

1. Verify the package contents.

2. Attach mSATA Device by inserting the mSATA card and securing the two screws to hold the mSATA card in place.

3. The device is ready to be integrated into your system.

MRK-MST250/UGT-MST100 Changing screws mount for other size mSATA card (27mm or 70mm card).

Pull side wall back slightly to unlock latch holding PCB.

PCB lock by latch on side wall.

1. Pull side wall back slightly to unlock latch holding PCB and lift the PCB out of the housing for all 4 locking latch.

2. Look on the back of the Printed Circuit(PCB) for the mSATA card mount (at 50mm position).

3. Remove the screws and washer holding the mSATA card mount.

4. Move the card mount to the right position that matches your mSATA card and secure back the screws and washer that holds the card mount.

5. Secure the card mount back to the correct position using the screws remove in step #3.

6. Attach mSATA Device by inserting the mSATA card and securing the two screws to hold the mSATA card in place.